

E Cores (9495111002)



Part Number: 9495111002

95 E CORE SET

The E core geometry offers an economical design approach for inductive applications in a variety of power designs.

E cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicated is per pair or set.

Weight: 40 2 (g)

weign	<u></u> 40.2 (<u>g)</u>				
Dim	mm	mm tol	nominal inch	inch misc.		
A	33	±0.60	1.299		Chart Legend □ Σl/ A : Core Constant, l _e : Effective Path Length, A _e : Effective Cross- Sectional Area, Effective Core Volume	V
В	14	±0.30	0.551			
С	12.7	±0.30	0.5			
D	9.6	±0.30	0.378			
Е	22.8	min	0.898	min		
F	9.7	±0.30	0.382			
A _L : Explai		tance Factor		= product class a	and 3 & 4 = material grade.	

Electrical Properties					
$A_L(nH)$	$5000 \pm 25\%$				
Ae(cm ²)	1.19				
$\Sigma l/A(cm^{-1})$	5.6				
l _e (cm)	6.65				
$V_e(cm^3)$	7.9				
$A_{min}(cm^2)$	1.12				

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288

888-324-7748 845-895-2055 Fax: 845-895-2629 ferrites@fair- rite.com www.fair- rite.com